

Specifications	EP2500C	EP2500CX	EP3800CX	EP5000CX	EP6500CX	EP6500CXS
AC frequency	50Hz	50Hz	50Hz	50Hz	50Hz	50Hz
AC output voltage	220V	220V	220V	220V	220V	220V
Rated AC output	2.0kVA	2.0kVA	2.8kVA	4.0kVA	5.0kVa	5.0kVa
Maximum AC output	2.2kVA	2.2kVA	3.1kVA	4.5kVA	5.5kVa	5.5kVa
Model	GX160K1	GX160K1	GX240K1	GX340K1	GX390K1	GX390K1
DC Output	12V-8.3A	12V-8.3A	12V-8.3A	12V-8.3A	12V-8.3A	12V-8.3A
Engine type	Air-cooled, 4-stroke, OHV single cylinder	Air-cooled, 4-stroke, OHV single cylinder	Air-cooled, 4-stroke, OHV single cylinder	Air-cooled, 4-stroke, OHV single cylinder	Air-cooled, 4-stroke, OHV single cylinder	Air-cooled, 4-stroke, OHV single cylinder
Displacement	163cm3	163cm3	242cm3	337cm3	389cm3	389cm3
Ignition system	Transistorised magneto	Transistorised magneto	Transistorised magneto	Transistorised magneto	Transistorised magneto	Transistorised magneto
Starting system	Recoil	Recoil	Recoil	Recoil	Recoil	Recoil
Fuel tank capacity (litres)	3.7	15	25	25	25	25
Maximum engine power output @3 600rpm	5.5PS (4.1kW)	5.5PS (4.1kW)	8.0PS (5.9kW)	11.0PS (8.1kW)	13.0PS (9.6kW)	13.0PS (9.6kW)
Continuous operating hours	2.8	13	13	10	9.2	9.2
Operating noise level @ 7m	67dB	65dB	68dB	70dB	72dB	72dB
Dry weight	36kg	45kg	68kg	82kg	85kg	89kg
Dimensions (L x W xH)	590 x 430 x 435mm	590 x 430 x 435mm	680 x 510 x 540mm	680 x 510 x 540mm	680 x 510 x 540mm	680 x 510 x 540mm
Automatic voltage regulator	Yes	Yes	Yes	Yes	Yes	Yes
Fuel gauge	-	Yes	Yes	Yes	Yes	Yes
Voltmeter	-	Yes	Yes	Yes	Yes	Yes
Oil alert	Yes	Yes	Yes	Yes	Yes	Yes
AC circuit breaker	Yes	Yes	Yes	Yes	Yes	Yes
Large capacity air cleaner	-	Yes	Yes	Yes	Yes	Yes
Accessory AC plug	Yes	Yes	Yes	Yes	Yes	Yes
Electric Starter	-	-	-	-	-	Yes

Features:

- Honda's AVR system automatically compensates for power fluctuations
- Low noise and low vibration, top-level fuel efficiency
- High output performance
- Oil alert system stops the engine automatically when oil level is too low
- Large-size aircleaner ensures excellent air intake efficiency for optimum engine power output
- Large'silent' mufflers minimize engine noise
- Easy-to-use AC/DC circuit breakers cut the power in the event of electrical overload while leaving the main power switch on
- Sturdy frame with upper guard pipes protects the machine, while making it easier to transport

- Backlight voltmeter allows you to check the generator output even in the dark
- Large fuel gauge allows you to check fuel level at a glance